

GENERATOR SPECIFICATION

Voltage	230/115
Phase	1
Frequency	50Hz
Prime Power (PRP)	2.7 kVA / 2.2 kW
Alternator	NSM K100C
Alternator Type	Brushless - Smooth Waveform
Fuel tank capacity	3.1 Litres
Autonomy 75% load	3.1 Hours
LWA	94
dBA @ 7M	69

ENGINE SPECIFICATION

Engine	Honda GX160
Emissions certified	EU Stage V
Cylinders	Single
Distribution	O.H.V.
Aspiration	Naturally aspirated
Cooling	Air
Displacement	163 cm ³
Rpm	3000
Starting system	Recoil
Fuel	Unleaded 86 octane or higher



DIMENSIONS (mm)

DIMENSIONS (mm)			WEIGHT (KG)
Length	Width	Height	41
610	420	415	



CONTROL BOX

- 1 x 16A 230V & 1 x 16A 115V BS4343 sockets.
- Reset circuit breaker overload protection.
- Voltage selector switch.

STANDARD FEATURES

- Oil alert/low oil shutdown.
- 3 Year engine warranty (Limited).
- Full wrap-around frame.
- Brushless smooth waveform alternator.

OPTIONS

- AVR (Automatic Voltage Regulator).
- Electric start.
- Long run tank.
- Single voltage.
- Trolley kit.*

* Different model used to illustrate trolley option.



POWER DEFINITION

Prime Power (PRP) : Applicable for supplying power to varying electrical load for unlimited hours in accordance ISO 8528-1 under the agreed operating conditions with the maintenance intervals and procedures being carried out as prescribed by the manufacturers.